

SWITCHLITE CC PROGRAMMER

Basic programming tool

Art. no. 96240295

Application

The Switchlite CC Programmer is a compact infrared remote control used for the basic programming of IR enabled Sensalite products. The programming is done remotely and therefore can be operated from the ground (7m is the IR range).



Functional description

Depending on the product that has to be programmed, the Switchlite CC Programmer can be used to setup features and parameters such as: Timeout, lux on level, lux off level, sensitivity, walk test, load type selection, burn-in, presence/absence mode. Basic control of the lights is also possible with On/Off and Raise/Lower functions. The Switchlite CC Programmer may include settings that are not used on the device being programmed. Refer to the individual device's Installation Instruction for default and special settings.

Technical data

Dimensions	86 x 67 x 4 (L x W x H, in mm)
Weight	Approx. 0.017 kg
Type of battery	3Vdc lithium battery CR2025 (supplied with unit)
IR range	7m
Operating temperature	0 to 35°C
Humidity	5 to 95% non-condensing
Compliance	EMC-2004/108/EC